

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Эл. почта: adm@nt-rt.ru || Сайт: <http://lambda.nt-rt.ru>



Model name

SWS150-5
Series Name Output Power Type Output voltage

Features

- All models conform to EN61000-3-2. (SWS100/150/300/600 with integral active PFC filter)
- Worldwide safety agency approvals: CE marking for LVD, UL/CSA/EN60950, EN50178
- EMI : Conform to EN55011-B, EN55022-B, FCC-B
- EMS: Conform to EN61000-4-2,3,4,5,6,8,11
- Screw terminal for input/output connections.

Specifications

Model	SWS50	SWS75	SWS100	SWS150	SWS300A	SWS300	SWS600
Input Voltage Range	85~265VAC (47-63Hz) or 120~370VDC						
Nominal Output Power (Refer to Product lineup)	50W	75W	100W	150W	300W	300W	600W
Nominal Output Voltage	3.3 , 5 , 12 , 15 ,24V				3.3,4,5,7.5,12,15,24,28,36,48V		3.3,5,12,15,24,36,48V
Output Voltage Range	±10%				3.3V: 2.97 -3.96V 4V: 3.6 -4.8V 5V: 4.5 -6.0V 7.5V: 6.0 -9.0V 12V: 9.6 -13.2V 15V: 13.2 -18.6V 24V: 20 -28.8V		3.3V: 2.97 -3.96V 5V: 4.5 -6.0V 12V: 9.6 -13.2V 15V: 13.2 -18.6V 24V: 20 -28.8V 36V: 28.8 -40V 48V: 40 -57.6V

					28V: 22.4-33.6V 36V: 28.8-40V 48V: 40 -57.6V		
Operating Temperature	-10~+60°C (Refer to Output Derating Curve)				-10 ~ +65°C (Refer to Output Derating Curve)		
Safety	Approved by UL/CSA/EN60950,EN50178,CE Marking for LVD						
EMI	Built to meet FCC-Class B,EN55011/EN55022-B						
Immunity	Built to meet EN61000-4-2,-3,-4,-5,-6,-8,-11						
Weight (g)	400	480	600	750	950	950	2000
Dimension (mm)	37 x 92 x 159	43 x 94 x 170	45 x 96 x 188	51 x 99 x 198	52 x 102 x 198	52 x 102 x 198	92 x 120 x 190

Product lineup

		Nominal Output Voltage	Maximum Output Current	Maximum Output Power
SWS50	SWS50-3	3.3V	10A	33W
	SWS50-5	5V	10A	50W
	SWS50-12	12V	4.3A	51.6W
	SWS50-15	15V	3.5A	52.5W
	SWS50-24	24V	2.1A	50.4W
SWS75	SWS75-3	3.3V	15A	49.5W
	SWS75-5	5V	15A	75W
	SWS75-12	12V	6.3A	75.6W
	SWS75-15	15V	5.0A	75W
	SWS75-24	24V	3.2A	76.8W
SWS100	SWS100-3	3.3V	20A	66W
	SWS100-5	5V	20A	100W
	SWS100-12	12V	8.5A	102W
	SWS100-15	15V	6.7A	100.5W
	SWS100-24	24V	4.3A	103.2W
SWS150	SWS150-3	3.3V	30A	99W
	SWS150-5	5V	30A	150W
	SWS150-12	12V	12.5A	150W
	SWS150-15	15V	10A	150W
	SWS150-24	24V	6.3A	151.2W
SWS300A	SWS300A-3	3.3V	55A	181.5W
	SWS300A-4	4V	55A	220W
	SWS300A-5	5V	55A	275W
	SWS300A-7R5	7.5V	40A	300W
	SWS300A-12	12V	26A	312W
	SWS300A-15	15V	21A	315W
	SWS300A-24	24V	13A	312W
	SWS300A-28	28V	11A	308W
	SWS300A-36	36V	8.8A	313.2W
	SWS300A-48	48V	6.7A	321.6W
SWS300	SWS300-3	3.3V	55A	181.5W
	SWS300-5	5V	55A	275W
	SWS300-12	12V	26A	312W

	SWS300-15	15V	21A	315W
	SWS300-24	24V	13A	312W
	SWS300-36	36V	8.7A	313.2W
	SWS300-48	48V	6.7A	321.6W
SWS600	SWS600-3	3.3V	100A	330W
			Peak Output Current(*1) 120A	Peak Output Power(*1) 396W
	SWS600-5	5V	100A	500W
			Peak Output Current(*1) 120A	Peak Output Power(*1) 600W
	SWS600-12	12V	50A	600W
	SWS600-15	15V	40A	600W
	SWS600-24	24V	25A	600W
	SWS600-36	36V	16.7A	601.2W
	SWS600-48	48V	12.5A	600W

(*1)Operating period at peak output current is less than 5sec.(Duty<=0.35).

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93