

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Эл. почта: adm@nt-rt.ru || Сайт: <http://lambda.nt-rt.ru>



Model name

EVS 36 - 8R4 /R

Series Name

Rated Output Voltage

Option

Blank : Standard type

/R : Remote ON/OFF control

Rated Output Current

(ex) 8R4 : 8.4A

Features

Trimmers on power supply allow presetting of charge current and charge voltage to implement constant current constant voltage charging
300 W model features fanless design

Various output voltage ratings to match storage system voltages are available

For 12 V storage systems: 18 V output type *

Only available as 300 W model

For 24 V storage systems: 36 V output type

For 48 V storage systems: 57 V output type

Compliant with UL 60950-1 and EN60950-1 safety standards

● Developed the backflow prevention module

Model: EVS-RP6020

Low loss: Due to using MOS-FET, 72% reduction of forward voltage comparing with schottky-barrier diode.

(Input: 7~60VDC, 20Amax, Reverse current: 50μAmax)

Inside loss: 4Wmax, Convection cooling,

Size: 50x26x77.5)



Specifications

Model	EVS18-16R7	EVS36-8R4	EVS57-5R3	EVS36-16R7	EVS57-10R6
Input Voltage Range	85~265VAC / 120~370VDC			85~265VAC / 120~330VDC	
Constant Voltage Mode Rated Voltage (Adjustable range)	18VDC (12~18VDC)	36VDC (24~36VDC)	57VDC (48~57VDC)	36VDC (24~36VDC)	57VDC (48~57VDC)
Constant Current Mode Rated Current 100 VAC (200 VAC)	16.7A (16.7A)	8.4A (8.4A)	5.3A (5.3A)	15.3A (16.7A)	9.7A (10.6A)
Rated Current Adjustable Range 100 VAC (200 V AC)	8.35~16.7A (8.35~16.7A)	4.2~8.4A (4.2~8.4A)	2.65~5.3A (2.65~5.3A)	8.35~15.3A (8.35~16.7A)	5.3~9.7A (5.3~10.6A)

Maximum Output Power	300W	600W
Remote ON/OFF Control	Option (/R)	
Parallel/Series Operation	Possible	
Safety	UL60950-1, EN60950-1	
Cooling	Convection cooling	Forced air by blower fan
Outline	PC Board Type	Unit Type
Dimension(WxHxD)mm	84 x 42 x 180	120 x 61 x 190

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93