

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Эл. почта: adm@nt-rt.ru || Сайт: <http://lambda.nt-rt.ru>



Model name

LWT 15 H - 5 2 2		
Names of series		Output voltage
Total Output power		522: 5V, +12V, -12V
15H: 17W type		5FF: 5V, +15V, -15V
30H: 30W type		525: 5V, +12V, -5V
50H: 50W type		

Features

- CE marking (Low Voltage Directive)
- Wide input voltage range : 85~265VAC universal input
- WattBox output design
- 9 models, Triple output 17W~50W
Low profile : Approx. 1 inch (26mm)
- Isolation between CH1 (5V) and CH
- G3 : 2 year warranty

Specifications

Input voltage range	AC85~265V (47~440Hz) DC110~330V universal input
Output voltage range	CH1 : +5%, CH2 : Fixed
Cooling	Convection cooling
Operating ambient temperature	0~+60°C Output derating, 0~+40°C :100%, +50°C :80%, +60°C : 60%
Withstand voltage	Input-output : 3kVAC, input-FG : 2kVAC for 1min.
Safety standard	Approved by UL1950, CSA234 and EN60950
EMI	Conforms to FCC class B and VDE class B
Functions	Over voltage protection (CH1), Over current protection

Product lineup

Model name		CH	Nominal output voltage	Max. output current	Max. output power	Total max. output power
LWT15H	LWT15H-5FF	CH1	5V	0.5-3.0A	15.0W	17.0W
		CH2	+15V	0.6A	9.0W	
		CH3	-15V	0.4A	6.0W	
	LWT15H-522	CH1	5V	0.5-3.0A	15.0W	17.0W
		CH2	+12V	0.6A	7.2W	
		CH3	-12V	0.4A	4.8W	
	LWT15H-525	CH1	5V	0.5-3.0A	15.0W	17.0W
		CH2	+12V	0.6A	7.2W	
		CH3	-5V	0.4A	2.0W	

LWT30H	LWT30H-5FF	CH1	5V	0.7-5.0A	25.0W	30.0W
		CH2	+15V	1.2A	18.0W	
		CH3	-15V	0.6A	9.0W	
	LWT30H-522	CH1	5V	0.7-5.0A	25.0W	30.0W
		CH2	+12V	1.2A	14.4W	
		CH3	-12V	0.6A	7.2W	
	LWT30H-525	CH1	5V	0.7-5.0A	25.0W	30.0W
		CH2	+12V	1.2A	14.4W	
		CH3	-5V	0.6A	3.0W	
LWT50H	LWT50H-5FF	CH1	5V	1.0-8.0A	40.0W	50.0W
		CH2	+15V	1.5A	22.5W	
		CH3	-15V	1.0A	15.0W	
	LWT50H-522	CH1	5V	1.0-8.0A	40.0W	50.0W
		CH2	+12V	1.5A	18.0W	
		CH3	-12V	1.0A	12.0W	
	LWT50H-525	CH1	5V	1.0-8.0A	40.0W	50.0W
		CH2	+12V	1.5A	18.0W	
		CH3	-5V	1.0A	5.0W	

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93