




Model name



Features

- CE marking (Low Voltage Directive)
- Compact linear power supply Low ripple & noise : 1mV (rms), 3mV (pk-pk)
- Low leakage current : 50μA
- Wide operating temperature range : -20~+71°C
- Input voltage range
100 / 115 / 200 / 230VAC(User selectable)
- Output current balancing in running in parallel
- G2 : 2 year warranty

Specifications

Input voltage range	100VAC : 85~115VAC, 115VAC : 98~132VAC, 200VAC : 170~230VAC, 230VAC : 195~265VAC (User selectable)
output voltage range	10%
Line regulation	Line regulation : 0.01% (Within input voltage range at constant load)
Load regulation	Load regulation : 0.03% (No load tu full load at constant input voltage)
Maximum ripple & noise	1mV(rms) 3mV(pk-pk)
Cooling	Convection Cooling
Operating ambient temperature	-20~+71°C -20°C : 60%, 0~+50°C : 100%, +60°C : 60%, +71°C : 40%
Withstand voltage	Input-output : 3.75kVAC, input-FG : 2.5kVAC
Safety standard	Approved by UL1950, CSA234 and EN60950
EMI	Conforms to VCCI-A, FCC-B, VDE-B
Functions	Over voltage protection, Over current protection, Remote sensing, Output current balancing NNS50 : Remote ON/OFF control

Product lineup

Model name		Nominal output voltage	Max. output current	Max. output power
NNS15	NNS15-5	5V	3A	15W
	NNS15-12	12V	1.7A	20.4W
	NNS15-15	15V	1.4A	21W
	NNS15-24	24V	0.9A	21.6W
NNS30	NNS30-5	5V	6A	30W
	NNS30-12	12V	4A	48W
	NNS30-15	15V	3.4A	51W
	NNS30-24	24V	2.3A	55.2W
NNS50	NNS50-5	5V	10A	50W
	NNS50-12	12V	6.5A	78W
	NNS50-15	15V	5.5A	82.5W
	NNS50-24	24V	3.8A	91.2W

Архангельск (8182)63-90-72
 Астана +7(7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06
 Ижевск (3412)26-03-58
 Казань (843)206-01-48

Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54

Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93