

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижегород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Эл. почта: adm@nt-rt.ru || Сайт: <http://lambda.nt-rt.ru>



Model name

SWT 30 - 5 2 2

Names of series	Output power	Nominal output voltage
		522 : 5V, +12V, -12V
		5FF : 5V, +15V, -15V
		525 : 5V, +12V, -5V

Features

- CE marking (Low Voltage Directive)
- Defact standard size in computer market
30W,40W : 3 x 5 inch
65W : 3.5 x 6 inch
- Wide input voltage range :
30W,40W,100W type : 85~265VAC universal input
65W type : 100 / 200VAC auto-selectable
- Compact and low price
- G6 : 1 year warranty

Specifications

Input voltage range	SWT30,40,100 : AC85~265V (47~63Hz),110~340VDC universal input SWT65 : AC85~132 / 170~265V (47~63Hz) auto-selectable
Output voltage range	Fixed
Cooling	Convection cooling
Operating ambient temperature (Standard mounting)	0~+60dp Output derating 0~+50°C : 100%, 60°C : 70%
Withstand voltage	Input-output : 3kVAC, Input-chassis : 2.5kVAC, Output - chassis : 500VAC for 1min
Safety standard	Approved by UL1950 and CSA950,and EN60950,Built to meet DENTORI
EMI	Built to meet EN-55011-B,EN55022-B,VCCI-classB and FCC class B
Peak output current	SWT30 CH1 : +5V 2A (peak 3A) CH2 : +12V 1.5A (peak 3A) / +15V 1A (peak 2.2A) SWT40 CH1 : +5V 3A (peak 4.5A) CH2 : +12V 2A (peak 3A) / +15V 1.5A (peak 2.4A)
Functions	Over voltage protection (CH1), Over current protection

Product lineup

Model name		CH	Nominal output voltage	Output current	Max. peak output current (Note1)	Nominal output power	Max. output power
SWT30	SWT30-522	CH1	+5V	0.2 - 2A	3A	31.6W	49.6W
		CH2	+12V	0.4 - 1.5A	3A		
		CH3	-12V	0.3A	-		
	SWT30-5FF	CH1	+5V	0.2 - 2A	3A	29.5W	47.5W
		CH2	+15V	0.4 - 1A	2.2A		
		CH3	-15V	0.3A	-		
	SWT30-525	CH1	+5V	0.2 - 2A	3A	29.5W	47.5W
		CH2	+12V	0.4 - 1.5A	3A		

		CH3	-5V	0.3A	-		
SWT40	SWT40-522	CH1	+5V	0.2 - 3A	4.5A	42.6W	54.6W
		CH2	+12V	0.3 - 2A	3A		
		CH3	-12V	0.3A	-		
		CH3	-12V	0.3A	-		
	SWT40-5FF	CH1	+5V	0.2 - 3A	4.5A	42.0W	51.6W
		CH2	+15V	0.3 - 1.5A	2.4A		
		CH3	-15V	0.3A	-		
	SWT40-525	CH1	+5V	0.2 - 3A	4.5A	40.5W	51.6W
		CH2	+12V	0.3 - 2A	3A		
		CH3	-5V	0.3A	-		
SWT65	SWT65-522	CH1	+5V	0.3 - 6A	-	66W	-
		CH2	+12V	2.5A	-		
		CH3	-12V	0.5A	-		
	SWT65-5FF	CH1	+5V	0.3 - 6A	-	64.5W	-
		CH2	+15V	1.8A	-		
		CH3	-15V	0.5A	-		
	SWT65-525	CH1	+5V	0.3 - 6A	-	62.5W	-
		CH2	+12V	2.5A	-		
		CH3	-5V	0.5A	-		
SWT100	SWT100-522	CH1	+5V	0.5 - 8A	-	97.6W	-
		CH2	+12V	4A	-		
		CH3	-12V	0.8A	-		
	SWT100-5FF	CH1	+5V	0.5 - 8A	-	100W	-
		CH2	+15V	3.2A	-		
		CH3	-15V	0.8A	-		
	SWT100-525	CH1	+5V	0.5 - 8A	-	92W	-
		CH2	+12V	4A	-		
		CH3	-5V	0.8A	-		

Note1 : Duration at peak current : 10 seconds max. (Duty : 0.3 max.)

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижегород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Эл. почта: adm@nt-rt.ru || Сайт: <http://lambda.nt-rt.ru>