

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижегород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Эл. почта: adm@nt-rt.ru || Сайт: <http://lambda.nt-rt.ru>

Model name



VS 30C - 5

Series Name | Output power | Output Voltage

Features

- Compact size
Input : 85~132VAC
- EMI : Conforms to VCCI-class B and FCC class B
- 2 year warranty

Specifications

Input voltage range	85~132VAC (47~440Hz), 110~175VDC
Output voltage range	±10%
Cooling	Convection cooling
Operating ambient temperature	-10~+60°C (-10~+50°C : 100%、+60°C : 70%)
Withstand voltage	Input-output : 2kVAC, input-chassis : 2kVAC, output-chassis : 500VAC for 1min
Safety standard	Approved by UL60950-1、CSA C22.2 No.60950-1、EN60950-1(TUV) ,Built to meet DENAN
EMI	Built to meet VCCI-class B and FCC class B
Functions	Over voltage protection, Over current protection

Product lineup

Model name	3.3V	5V	12V	15V
	Nominal output voltage current	Nominal output voltage current	Nominal output voltage current	Nominal output voltage current
VS10C	3.3V 2.0A	5V 2.0A	12V 0.85A	15V 0.7A
VS15C	3.3V 3.0A	5V 3.0A	12V 1.25A	15V 1.0A
VS30C	3.3V 6.0A	5V 6.0A	12V 2.5A	15V 2.0A

Model name	24V	36V	48V
	Nominal output voltage current	Nominal output voltage current	Nominal output voltage current
VS10C	24V 0.5A	-	-
VS15C	24V 0.7A	-	-
VS30C	24V 1.3A	36V 0.9A	48V 0.7A