

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана +7(7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижегород (831)429-08-12
Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54

Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Эл. почта: adm@nt-rt.ru || Сайт: <http://lambda.nt-rt.ru>



Model name

ZWS 150 BAF - 5 / □

Series Name Rated Output Voltage Output power type

Option

Blank: Standard type.
A: With chassis and cover model.
L: With chassis model.
CO2: Both sides coating type.
FV: Volumeless type
(Only 12V, 24V, 48V output of 50BAF-150BAF)
R: With remote ON/OFF control model.
(100BAF, 150BAF, 300BAF only)
T: With terminal model (300BAF only)

Features

- PFHC
- High efficiency and low standby power
- Super small size, Light weight
- 100% load at 50°C, suitable for industrial equipment.(50BAF-150BAF only)
- 5 Years warranty (conditions applied)

Specifications

Input voltage range	85 - 265VAC (47 - 63Hz) or 120 - 370VDC universal input
Cooling	Convection cooling
Operating ambient temperature	no Cover (50BAF~150BAF) -10°C~+50°C : 100%, +60°C : 75%, +70°C : 50% (300BAF) -10°C~+45°C : 100%, +50°C : 88%, +60°C : 64%, +70°C : 40% with Cover (50BAF~150BAF) -10°C~+40°C : 100%, +50°C : 75%, +60°C : 50% (300BAF) -10°C~+30°C : 100%, +40°C : 80%, +50°C : 60%, +60°C : 40%
Withstand voltage	Input-output : 3kVAC, Input-chassis : 2kVAC, Output-chassis : 500VAC for 1min.
Safety standard	Approved by UL60950-1, CSA60950-1, EN60950-1, EN50178(OV II), Conforms to DENAN at 100VAC only.
EMI	Conforms to EN55011-B, EN55022-B, VCCI-B, FCC-B
Functions	Over voltage protection, Over current protection

Product lineup

	3.3V		5V		12V		15V		24V		36V		48V	
	Out put cur-rent	Output power	Out put cur-rent	Output power	Out put cur-rent	Output power	Out put cur-rent	Output power	Out put cur-rent	Output power	Out put cur-rent	Output power	Out put cur-rent	Output power
ZWS 50BAF	10A	33.0W	10A	50.0W	4.3A	51.6W	3.5A	52.5W	2.1A	50.4W	-	-	1.1A	52.8W
ZWS 75BAF	15A	49.5W	15A	75.0W	6.3A	75.6W	5.0A	75.0W	3.2A	76.8W	-	-	1.6A	76.8W
ZWS 100BAF	20A	66.0W	20A	100.0W	8.5A	102.0W	6.7A	100.5W	4.3A	103.2W	-	-	2.1A	100.8W
ZWS 150BAF	30A	99.0W	30A	150.0W	12.5A	150.0W	10A	150.0W	6.3A	151.2W	-	-	3.2A	153.6W
ZWS 300BAF	-	-	-	-	25A	300.0W	20A	300.0W	12.5A	300.0W	8.4A	302.4W	6.3A	302.4W

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
 Астана +7(7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06
 Ижевск (3412)26-03-58
 Казань (843)206-01-48

Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81

Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54

Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93